

1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

USER GROUP: 2-5 Years

RECOMMENDED CREW: 4 People

TOOLS REQUIRED:

• T-30, 3/16" Allen wrench, #2 Square Drive

Level

Drill Bits: 3/32", 7/64", 5/32", 21/64"
High Speed 3/8" Electric Drill with Clutch

NOTE: Use of any other driver may result in damage to

product, tool, and/or hardware! INSTALLATION TIME: 3 Hours

WEIGHT: 822 lbs.


CONCRETE REQUIRED: None



Customer is responsible for verifying materials received by comparing received items with packing list. If any parts are missing or damaged, including documentation, contact your local sales representative immediately.

Supplier is not responsible for items discovered missing after 72 hours from time of delivery.

Before beginning installation, all installers must read and understand the Installation Introduction manual as supplied. If you did not receive a copy, or if you have any questions regarding any information in the Installation Instructions or this Installation Guideline, contact your local sales representative.










Countryside Cottage • UPLAY-038

A PLAYCORE Company

ITEM	Part No.	QTY	DESCRIPTION
1	AFB-31124XX	1	Widmnt - R-town School/House Back Panel Frame
2	AFB-31123XX	2	Wildmnt - R-town School/House Side Panel Frame
3	TRA0162XX	1	Pre-Assem R-Town Deck
4	RSA-0625XX	1	Pre-Assem R-Town® Cottage Chimney
5	AFB-31130XX	1	Widmnt - R-town School/House Front Panel Frame
6	RSP-1882XX	2	Sheet - R-Town® Cottage Side Wall Panel
7	RSP-1885XX	1	Sheet - R-Town® Cottage Back Wall Panel
8	RSP-1884XX	1	Sheet - R-Town® Cottage Front Wall Panel
9	RSP-1674XX	2	Sheet - R-Town Roof
10	RSP-1669XX	1	Sheet - R-Town School Porch Roof Support
11	RSP-1677XX	1	Sheet - R-Town Porch Roof (Left Side)
12	RSP-1678XX	1	Sheet - R-Town Porch Roof (Right Side)
13	AFB-31145XX	1	Wildmnt - R-town Porch Roof Support Post (Right)
14	AFB-31147XX	1	Widmnt - R-town Porch Roof Support Post (Left)
15	AFB-31149XX	2	Widmnt - R-town Roof Support Bottom
16	AFB-31150XX	2	Widmnt - R-town Roof Support Middle
17	AFB-31151XX	2	Widmnt - R-town Roof Support Top
18	HWS0021	60	Screw - 1/4" x 1" Self Tapping Torx w/Patch
19	HWS0298	29	Screw - 1/4" x 1-1/2" RSS SS
20	HWWR0092	4	Washer 3/8" ID x 1-1/4" OD Flat SS
21	HWS0107	2	Screw #8 x 1-5/8" Deck SS
22	HWB0344	4	Bolt - 5/16"-18 x 3/4" ABH SS
23	HWN0149	18	Nut - 5/16 - Zn Insert Type I
24	HWWR0114		Washer 5/16 ID x 3/4 OD Flat .05

14 Bolt - 5/16"-18 x 1-1/2" ABH SS

81 3/8" x 1-1/4" Self Tapping Torx w/patch



MODEL NUMBER: UPLAY-038

DATE: 01/29/20

HWB0352

HWS0081




1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 1

Place deck into final location. Deck will not be moved once placed. Refer to the site plan drawing and site elevation drawing for placement of all structures. Installer is responsible for proper location of all structures. Either end of deck can be designated as the front.







A PIAYCORE Company 1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 2 Mount rear frame and side frame. Place rear frame 3/4" from rear edge of deck. Center rear frame on deck. Place side frame 1/2" from side edge of deck. See Detail 2-1. At bottom plates on side frame, drill nine (9) Drill 3/16" Pilot Hole 3/16" pilot holes through bottom plates into deck. Secure with nine (9) Secure With 1/4" x 1-1/2" RSS. At edge plates on side frame, secure with three (3) 1/4" x 1-1/2" RSS 1/4" x 1" self-tapping Torx. Pilot holes are not required. Typ. 9 Bracing may be required until all frames are mounted. Secure With 1/4" x 1" Self-Tapping Torx Typ. 3 Detail 2-1 Side Frame Rear Frame Rear Frame Side Frame from Deck End from Deck Edge






1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 3

Secure side frame to rear frame. Place side frame 1/2" from side edge of deck. At bottom plates on side frame, drill nine (9) 3/16" pilot holes through bottom plates into deck. Secure with nine (9) 1/4" x 1-1/2" RSS. At edge plates on side frame, secure with three (3) 1/4" x 1" self-tapping Torx. Pilot holes are not required. Bracing may be required until all frames are mounted.



Drill 3/16" Pilot Hole Secure With 1/4" x 1-1/2" RSS Typ. 9




MODEL NUMBER: UPLAY-038 DATE: 01/29/20



INSTALLATION GUIDELINE

STEP 4

Secure front frame to side frames. Place front frame between side frames. At edge plates on side frames, secure with six (6) 1/4" x 1" self-tapping Torx. Pilot holes are not required. At edge plate on bottom of front frame, drill three (3) 3/16" pilot holes through plate and into deck. Secure with three (3) 1/4" x 1-1/2" RSS.












INSTALLATION GUIDELINE









1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 6 Secure with Mount chimney panel to rear panel. Align holes in chimney panel 5/16" x 3/4" Flat Washer with holes in rear panel. From chimney side, insert fourteen (14) and 5/16" x 1-1/2" 5/16" knock-in nuts into chimney panel. From inside rear panel, Allen Button Head Screw secure with fourteen (14) 5/16" x 3/4" flat washers and fourteen (14) Typ. 14 5/16" x 1-1/2" Allen button head screws. Insert 5/16" Knock-In Nut Typ. 14

MODEL NUMBER: UPLAY-038 DATE: 01/29/20



INSTALLATION GUIDELINE

STEP 7 Mount front panel. Set panel flush on deck edge. Center panel on front frame. At each pre-drilled hole in panel, drill one (1) 21/64" pilot hole through panel and into frame. Secure with one (1) 3/8" x 1-1/4" self-tapping security Torx. Typ. 23 locations.

> Drill 21/64" Pilot Hole, Secure With 3/8" x 1-1/4" Self-Tapping Security Torx Typ. 22




1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE


STEP 8

Mount right side panel. Set panel flush on deck edge. Place panel between front and rear panels. At each pre-drilled hole in panel edge, drill one (1) 21/64" pilot hole through panel and into frame. Secure with one (1) 3/8" x 1-1/4" self-tapping security Torx. Typ. 16 locations.



Drill 21/64" Pilot Hole Secure with 3/8" x 1-1/4" Self-Tapping Security Torx Typ. 16









1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 9

Mount left side panel. Set panel flush on deck edge. Place panel between front and rear panels. At each pre-drilled hole in panel edge, drill one (1) 21/64" pilot hole through panel and into frame. Secure with one (1) 3/8" x 1-1/4" self-tapping security Torx. Typ. 16 locations.

Drill 21/64" Pilot Hole Secure with 3/8" x 1-1/4" Self-Tapping Security Torx Typ. 16






1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com


INSTALLATION GUIDELINE

STEP 10

Mount left side roof supports. Roof supports are three lengths. Measure from ridge of front and rear frames to bar of each roof support and mark positions. See Detail 10-1. Secure each end of roof supports with two (2) 1/4" x 1" self-tapping Torx. Repeat for opposite ends of roof supports.

Detail 10-1






MODEL NUMBER: UPLAY-038







INSTALLATION GUIDELINE



MODEL NUMBER: UPLAY-038 DATE: 01/29/20





1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

Secure With 1/4" x 1"

Typ. 12


Self-Tapping Torx

INSTALLATION GUIDELINE


STEP 12


Mount right roof panel. Top edge of roof panel should be flush with frame ridges. See Detail 12-1. Center roof edges on front and rear frames. See Detail 12-2. Align countersunk holes in roof panel with roof support bars. At each countersunk hole, secure roof panel to roof supports with 1/4" x 1" self-tapping Torx. Typ. 12 locations.

Detail 12-1



Detail 12-2







INSTALLATION GUIDELINE 1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com A PLAYCORE Company STEP 13 Repeat STEP 12 for left roof panel. Secure With 1/4" x 1" Self-Tapping Torx Typ. 12



1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

Roof Edges

In Grooves

On Front Panel

STEP 14

Secure knock-in nuts into porch roof panels. Temporarily place porch roof panels into slots on front panel. Place porch support posts 1" from front edge of deck. Ensure posts are plumb. At the top end of each support post, drill two (2) 1/4" pilot holes through top end of support post and through porch roof panel. From shingle side of roof panel, insert two (2) 5/16" knock-in nuts.


Drill 1/4" Pilot Hole A Insert 5/16" Knock-In Nut From Shingle Side Typ. 2 Per Porch Roof Panel





1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE








A PIAYCORE Company

1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 16

Mount porch roof support. Ensure top edge of roof support is flush against roof panels. Ensure pre-drilled holes in roof support are centered on support posts. Drill four (4) 21/64" through panel and into support posts. Secure with four (4) 3/8" x 1-1/4" self-tapping security Torx.



MODEL NUMBER: UPLAY-038 DATE: 01/29/20






INSTALLATION GUIDELINE


STEP 17

Secure porch assembly to deck. Place porch assembly around front panel door. Place rear edges or porch roof into grooves on front panel. Place feet of support posts 1" from edge of deck. Ensure support posts are plumb. Drill two (2) 5/32" holes through support post foot into deck. Secure with two (2) 3/8" x 1-1/4" flat washers and two (2) 1/4" x 1-1/2" RSS. See Detail 17-1. Repeat for opposite support post.

A PAYCORE Company

Detail 17-1











INSTALLATION GUIDELINE

Roof Edges


In Grooves


STEP 18

Secure porch roof edge to front panel. From inside house, drill two (2) 7/64" pilot holes through pre-drilled holes in front panel into edge of roof panels. Secure with two (2) #8 x 1-5/8" deck screws. See Detail 18-1.

A PAYCORE Company














INSTALLATION GUIDELINE



MODEL NUMBER: UPLAY-038





1675 Locust Street Red Bud, IL 62278 • 888.403.7684 • Ultraplay.com

INSTALLATION GUIDELINE

STEP 20 Check all connections and ensure structure is stable. Installation is complete.

Place one (1) Age Appropriate Sticker on structure in a clearly visible location.

